



The classic Chevin A-Series amplifier is built in a steel and aluminium housing incorporating lateral Mosfets and the legendary Chevin Power Supply, this combination produces the traditional Chevin sound.

- High efficiency power supply design
- Lightweight and compact
- Excellent sonic quality
- Comprehensive protection system independent for each channel
- Anti-surge AC 'soft-start' circuit with automatic mute on power up

### Technical Specification

<b>RMS Power Output</b> into 4Ω (per channel) into 8Ω (per channel)	2500 W 1250 W
<b>Number of Channels</b>	2
<b>Power Bandwidth +0db, -3db</b>	2 Hz – 80 kHz
<b>Slew Rate in Excess of</b>	75 V / μS
<b>Gain</b>	X100
<b>Total Harmonic Distortion</b> typical @ 1db below clip 20 kHz @ 1db below clip	0,04 % 0,07 %
<b>Signal to Noise Ratio</b> Typical Reference Full Output, Unweighted Worst Case 10 Hz – 30 kHz	-125 dB -95 dB
<b>Crosstalk Typical</b>	-115 dB
<b>Damping Factor</b>	400
<b>Input Impedance Electronically Balanced</b>	10 kΩ
<b>CMRR (typical)</b>	-70 dB
<b>Input Sensitivity</b> Reference Full Output into 4 Ω	1V RMS
<b>Protection</b> Clipping, Load Below 2.4 Ω Shorted Output, DC or RF at Output	soft, dynamic linear immediate
<b>Power Consumption</b> 1/3 Power Typical Program	2,5 kVA
<b>50/60 Hz AC in Volts (internally selectable)</b>	220 – 240 V or 100 – 120 V
<b>Dimensions / Weight</b> H X W x D / Rack Units Net Weight	88 x 483 x 381 / 2U 14.0kg

