



The classic Chevin A-Series amplifier is built in a steel and aluminium housing incorporating lateral Mosfets and the legendary Chevin Power Supply, this combination produces the traditional Chevin sound.

- High efficiency power supply design
- Lightweight and compact
- Excellent sonic quality
- Comprehensive protection system independent for each channel
- Anti-surge AC 'soft-start' circuit with automatic mute on power up

### Technical Specification

<b>RMS Power Output</b>	
into 8Ω (per channel)	600 W
into 4Ω (per channel)	1000 W
<b>Number of Channels</b>	4
<b>Power Bandwidth +0db, -3db</b>	2 Hz – 80 kHz
<b>Slew Rate in Excess of</b>	75V / μS
<b>Gain</b>	x 65
<b>Total Harmonic Distortion</b>	
typical @ 1db below clip	0.04 %
20 kHz @ 1db below clip	0.07 %
<b>Signal to Noise Ratio</b>	
Typical Reference Full Output, Unweighted	-125 dB
Worst Case 10 Hz – 30 kHz	-95 dB
<b>Crosstalk Typical</b>	-115 dB
<b>Damping Factor</b>	400
<b>Input Impedance Electronically Balanced</b>	10 kΩ
<b>CMRR (typical)</b>	-70dB
<b>Input Sensitivity</b>	
Reference Full Output into 4 Ω	1V RMS
<b>Protection</b>	
Clipping, Load Below 2.4 Ω	Soft, Dynamic Linear
Shorted Output, DC or RF at Output	Immediate
<b>Power Consumption</b>	
1/3 Power Typical Program	2.2 kVA
<b>50/60 Hz AC in Volts</b>	220 – 240 V
<b>Dimensions / Weight</b>	
H X W x D / Rack Units	88mm x 483mm x 381mm / 2U
Net Weight	14 kg

